

## Family Charger

### North American Region

Download Instructions and Warranty Information

[English](#) | [Français](#) | [Español](#)

#### Product Detail:

**Designation:** Family Charger

**Color:** Black and Silver

**Charging Current:** 2 or 4 "AA" 1100mA (1 battery per bay)  
1 or 2 "AA-C-D" 1100mA (1 battery per bay)

6 or 8 "AA" 550mA (2 batteries per bay)

3 or 4 "AA-C-D" 550mA (2 batteries per bay)

1 to 4 "AAA" 450mA

2 or 4 "AAA" 450 mA

6 or 8 "AAA" 450 mA

1 to 2 "9V" 30mA

*Only one battery size can be charged per charging cycle. Do not charge different battery sizes at the same time*

**Trickle Charge:** "AA-C-D" 50mA

"AAA" 25mA

"9V" 2mA

**Shutoff Mechanism:** Delta V Detection and Timer Control

Delta V Detection 5mV per cell for "AA-AAA-C-D"

Max Timer Control 2 or 4 "AA" / 1 or 2 "AA-C-D" 3 hours

6 or 8 "AA" / 3 or 4 "AA-C-D" 6 hours

2 or 4 or 6 or 8 "AAA" 3 hours

1 to 2 "9V" 7 hours

**Charger Input :** DC 12V, 1A

**AC Adapter Input:** 100-240V AC 50/60Hz 0.35A

**AC Adapter Output:** DC 12V, 1A

**Weight (charger):** 460 grams (16.2 oz.)

**Dimensions (mm):** 72 x 203 x 111 (H x L x W)

**Volume (cm<sup>3</sup>):** 16223 (charger), 1248 (AC adapter)

**Safety Features:** Delta V Charging Cut Off

Short Circuit and Reverse Polarity Protection

Safety Timer to Prevent Over Charge

Bad Battery Detection



### EASY

- Drop batteries in the charger, close the lid, charging begins automatically
- Contacts auto-adjust
- LCD enables users to see charge status



### VERSATILE & FAST

- Charges:
- 4 AA in 3hr\* (2500 mAh)
  - 8 AA in 6hr (2500 mAh)
  - 4 AAA in 3hr\* (900 mAh)
  - 8 AAA in 6hr (900 mAh)
  - 4 C/D in 6hr (2500 mAh)
  - 9V 175 in 7hr (175 mAh)



### SAFE

- Power is only on when lid is closed
- Auto shut off feature when batteries are done



#### Before Using Your Charger:

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

**Best used with Energizer NiMH batteries.**

#### Important Notice

This datasheet contains information specific to products manufactured at the time of its publication.

©Energizer Holdings, Inc.

**Contents herein do not constitute a warranty.**